


75mm

BASIC INFORMATION




This device provides a shortcut to a smarter home by being applicable with any lighting device, both new and existing, and offering nice wireless lighting and ON/OFF control. Its functional dimensions makes it ideal for light switches in every space. It fits into standard wall boxes and helps turning your lighting into a smart one without any difficulties.

WARNINGS & SAFETY INSTRUCTIONS


The following must be read, kept, and observed before installation:

- The detector is for indoor use only.
- Improper use or installation of the device can cause SERIOUS INJURY, DEATH or LOSS/DAMAGE OF PROPERTY.
- Do not use in a manner other than outlined in this document is.
- The installation may only be carried out by a qualified electrician.
- Installation on flammable materials is not permitted.
- Do not install with power applied to device.
- Do not expose the device to moisture.


MOUNTING THE DEVICE



Fit inside the junction box and follow the connection diagram to connect to power, load and push button switch



— L - terminal for live lead
— N - terminal for neutral lead
— Out - output terminal of the dimmer (controlling connected light source)
— *A1 - terminal for push switch
— *A2 - terminal for grounding to the switch connected to the dimmer



— L - terminal for live lead
— N - terminal for neutral lead
— Out - output terminal of the dimmer (controlling connected light source)
— *A1 - terminal for push switch
— *A2 - terminal for grounding to the switch connected to the dimmer


CONFIGURATION

- Download the App
Search for TIS Control & download the app.
- Set up your hub (if not already set in the application).

- Go to Settings, and enter the default username and password.
- Go to the TIS-BEE configuration button, and follow the instructions.
- Add the Device
In the TIS-Bee configuration, press Add Device. Then, follow the instructions to add the device using the 2 available methods.

Select whichever method you prefer, and follow the instructions on the app.

TECHNICAL SPECIFICATIONS



Product Dimensions: 45mm*45mm*20.3mm
Voltage: 100-240V AC
Maximum Load: 400 W

Communication Protocol: Zigbee® SLL Network
Item Weight: 170g
Material: ABS Plastic

75mm


LEARNING ZIGBEE REMOTE

- Short press "Reset," button 4 times (Or reset power of the device 4 times) to start Learning mode (connected light flashes twice), 180 seconds timeout, repeat this step.
- Set the green power remote into Learning mode, please refer to its manual

DELETE LEARNING ZIGBEE REMOTE


- Short press "Reset," button 3 times (Or reset power of the device 3 times) to start delete Learning mode (connected light flashes slowly), 180 seconds timeout, repeat this step
- Set the paired green power remote into Learning mode, please refer to its manual
- Connected light will flash 4 times to indicate successful deleting

LED BEHAVIOR



LED Status	Description
LED blinks 5 times	Device is connecting
LED stays solid	Device is connected

RESET TO FACTORY DEFAULT




Short press "Reset" key for 5 times continuously or re-power on the device for 5 times continuously if the "Prog." key is not accessible

TROUBLESHOOTING


Problem	Possible Cause	Solution
Module not in pairing mode	Module is away from the hub, or there are obstacles	Move Module closer to the hub
	Module is connected to another hub network	Reset the module to factory default

Product specifications, size, shape, and prices are subject to change without notice, and actual product appearance may differ from that depicted on the packaging.

TIS TIS CONTROL LIMITED
RM 1502-09 Eassey Comm Bldg 253-261
Hennessy Rd Wanchai, Hong Kong
www.tiscontrol.com



TIS BEE User Manual



Please read the user manual carefully before operation